



by Schneider Electric

SAFETY GUIDE for Back-UPS™

SAVE THESE INSTRUCTIONS

IMPORTANT SAFETY INSTRUCTIONS – This manual contains important instructions that should be followed during installation and maintenance of APC by Schneider Electric equipment and batteries.

General Safety Information

- This UPS is intended for indoor use only.
- Do not operate this unit in direct sunlight, in contact with fluids, or where there is excessive dust or humidity.
- Be sure the air vents on the UPS are not blocked. Allow adequate space for proper ventilation.
- For a UPS with a factory installed power cord, connect the UPS power cable directly to a wall outlet. Do not use surge protectors or extension cords.
- The UPS cord shall be connected to an earthed mains socket outlet for safety reasons.
- **230 V models only:** In order to maintain compliance with the EMC regulations for products sold in Europe, output cords and network cables attached to the UPS must not exceed 10 meters in length.
- The UPS input ground conductor must be properly bonded to protective earth at the wall socket.
- Always recycle used batteries.
- Recycle the package materials or save them for reuse.
- This Safety Guide can be downloaded from APC by Schneider Electric Website, www.apc.com.

De-energizing safety

- The UPS contains internal batteries and may present a shock hazard even when disconnected from AC and DC power.
- Before installing or servicing the equipment check that the:
 - Input circuit breaker is in the OFF position.
 - Internal UPS batteries are removed.
 - XLBP battery modules, if connected, are disconnected.

Battery Safety

- Servicing of batteries should be performed or supervised by personnel knowledgeable about batteries and required precautions.
- When replacing batteries, replace with the same type and number of batteries or battery packs.
- Failed batteries can reach temperatures that exceed the burn thresholds for touchable surfaces.
- CAUTION: Do not dispose of batteries in a fire. The batteries may explode.
- CAUTION: Do not open or mutilate batteries. Released material is harmful to the skin and eyes. It may be toxic.
- CAUTION: A battery can present a risk of electrical shock and high short-circuit current. The following precautions should be observed when installing or replacing batteries:
 - Disconnect the charging source prior to connecting or disconnecting terminals.
 - Do not wear any metal objects including wrist watches and rings. Remove conductive jewelry such as chains, wrist watches and rings. High energy through conductive materials could cause severe burns.
 - Do not lay tools or metal parts on top of batteries.
 - Use tools with insulated handles.
 - Wear rubber gloves and boots.
 - Determine if battery is either intentionally or inadvertently grounded. Contact with any part of a grounded battery can result in electric shock and burns by high short-circuit current. The risk of such hazards can be reduced if grounds are removed during installation and maintenance by a skilled person.